

## Chip EMI Suppression Filter Design Kits



### ●EKEMBL03D (Chip Ferrite Beads 01005 Size / 0201 Size)

No.	Part Number	Quantity (pcs.)	Impedance typ. (at 100MHz, 20 degrees C)	Rated Current (mA)	DC Resistance (Ω) max.
1	<b>BLM02AG100SN1</b>	10	10Ω (Typ.)	500	0.1
2	<b>BLM02AG700SN1</b>	10	70Ω±25%	250	0.5
3	<b>BLM02AG121SN1</b>	10	120Ω±25%	200	0.8
4	<b>BLM03AG100SN1</b>	10	10Ω (Typ.)	500	0.1
5	<b>BLM03AG700SN1</b>	10	70Ω (Typ.)	200	0.4
6	<b>BLM03AG800SN1</b>	10	80Ω±25%	200	0.4
7	<b>BLM03AG121SN1</b>	10	120Ω±25%	200	0.5
8	<b>BLM03AG241SN1</b>	10	240Ω±25%	200	0.8
9	<b>BLM03AG601SN1</b>	10	600Ω±25%	100	1.5
10	<b>BLM03AG102SN1</b>	10	1000Ω±25%	100	2.5
11	<b>BLM03BB100SN1</b>	10	10Ω±25%	300	0.4
12	<b>BLM03BB220SN1</b>	10	22Ω±25%	200	0.5
13	<b>BLM03BB470SN1</b>	10	47Ω±25%	200	0.7
14	<b>BLM03BB750SN1</b>	10	75Ω±25%	200	1.0
15	<b>BLM03BB121SN1</b>	10	120Ω±25%	100	1.5
16	<b>BLM03BD750SN1</b>	10	75Ω±25%	300	0.4
17	<b>BLM03BD121SN1</b>	10	120Ω±25%	250	0.5
18	<b>BLM03BD241SN1</b>	10	240Ω±25%	200	0.8
19	<b>BLM03PG220SN1</b>	10	22Ω±25%	900	0.065
20	<b>BLM03PG330SN1</b>	10	33Ω±25%	750	0.090

### ●EKEMBL15J (Chip Ferrite Beads 0402 Size)

No.	Part Number	Quantity (pcs.)	Impedance typ. (at 100MHz, 20 degrees C)	Rated Current (mA)	DC Resistance (Ω) max.
1	<b>BLM15AG100SN1</b>	10	10Ω (Typ.)	1000	0.05
2	<b>BLM15AG700SN1</b>	10	70Ω (Typ.)	500	0.15
3	<b>BLM15AG121SN1</b>	10	120Ω±25%	500	0.25
4	<b>BLM15AG221SN1</b>	10	220Ω±25%	300	0.35
5	<b>BLM15AG601SN1</b>	10	600Ω±25%	300	0.60
6	<b>BLM15AG102SN1</b>	10	1000Ω±25%	200	1.00
7	<b>BLM15BA050SN1</b>	10	5Ω±25%	300	0.10
8	<b>BLM15BA100SN1</b>	10	10Ω±25%	300	0.20
9	<b>BLM15BA220SN1</b>	10	22Ω±25%	300	0.30
10	<b>BLM15BA330SN1</b>	10	33Ω±25%	300	0.40
11	<b>BLM15BA470SN1</b>	10	47Ω±25%	200	0.60
12	<b>BLM15BA750SN1</b>	10	75Ω±25%	200	0.80
13	<b>BLM15BB050SN1</b>	10	5Ω±25%	500	0.08
14	<b>BLM15BB100SN1</b>	10	10Ω±25%	300	0.10
15	<b>BLM15BB220SN1</b>	10	22Ω±25%	300	0.20

Continued on the following page.

## Chip EMI Suppression Filter Design Kits

 Continued from the preceding page.

No.	Part Number	Quantity (pcs.)	Impedance typ. (at 100MHz, 20 degrees C)	Rated Current (mA)	DC Resistance (Ω) max.
16	<b>BLM15BB470SN1</b>	10	47Ω±25%	300	0.35
17	<b>BLM15BB750SN1</b>	10	75Ω±25%	300	0.40
18	<b>BLM15BB121SN1</b>	10	120Ω±25%	300	0.55
19	<b>BLM15BB221SN1</b>	10	220Ω±25%	200	0.80
20	<b>BLM15BD750SN1</b>	10	75Ω±25%	300	0.20
21	<b>BLM15BD121SN1</b>	10	120Ω±25%	300	0.30
22	<b>BLM15BD221SN1</b>	10	220Ω±25%	300	0.40
23	<b>BLM15BD471SN1</b>	10	470Ω±25%	200	0.60
24	<b>BLM15BD601SN1</b>	10	600Ω±25%	200	0.65
25	<b>BLM15BD102SN1</b>	10	1000Ω±25%	200	0.90
26	<b>BLM15BD182SN1</b>	10	1800Ω±25%	100	1.40
27	<b>BLM15HD601SN1</b>	10	600Ω±25%	300	0.85
28	<b>BLM15HD102SN1</b>	10	1000Ω±25%	250	1.25
29	<b>BLM15HD182SN1</b>	10	1800Ω±25%	200	2.20
30	<b>BLM15HG601SN1</b>	10	600Ω±25%	300	0.70
31	<b>BLM15HG102SN1</b>	10	1000Ω±25%	250	1.10
32	<b>BLM15HB121SN1</b>	10	120Ω±25%	300	0.70
33	<b>BLM15HB221SN1</b>	10	220Ω±25%	250	1.00
34	<b>BLM15EG121SN1</b>	10	120Ω±25%	1500	0.095
35	<b>BLM15EG221SN1</b>	10	220Ω±25%	700	0.28
36	<b>BLM15GG221SN1</b>	10	220Ω±25%	300	0.70
37	<b>BLM15GG471SN1</b>	10	470Ω±25%	200	1.30
38	<b>BLM15GA750SN1</b>	10	75Ω±25%	200	1.30
39	<b>BLM15PG100SN1</b>	10	10Ω (Typ.)	1000	0.05
40	<b>BLM15PD300SN1</b>	10	30Ω±25%	2200	0.035
41	<b>BLM15PD600SN1</b>	10	60Ω±25%	1700	0.06
42	<b>BLM15PD800SN1</b>	10	80Ω±25%	1500	0.07
43	<b>BLM15PD121SN1</b>	10	120Ω±25%	1300	0.09

### ●EKEMBL18G (Chip Ferrite Beads 0603 Size)

No.	Part Number	Quantity (pcs.)	Impedance typ. (at 100MHz, 20 degrees C)	Rated Current (mA)	DC Resistance (Ω) max.
1	<b>BLM18AG121SN1</b>	10	120Ω±25%	500	0.18
2	<b>BLM18AG151SN1</b>	10	150Ω±25%	500	0.25
3	<b>BLM18AG221SN1</b>	10	220Ω±25%	500	0.25
4	<b>BLM18AG331SN1</b>	10	330Ω±25%	500	0.30
5	<b>BLM18AG471SN1</b>	10	470Ω±25%	500	0.35
6	<b>BLM18AG601SN1</b>	10	600Ω±25%	500	0.38
7	<b>BLM18AG102SN1</b>	10	1000Ω±25%	400	0.50
8	<b>BLM18BA050SN1</b>	10	5Ω±25%	500	0.20
9	<b>BLM18BA100SN1</b>	10	10Ω±25%	500	0.25
10	<b>BLM18BA470SN1</b>	10	47Ω±25%	300	0.55
11	<b>BLM18BA750SN1</b>	10	75Ω±25%	300	0.70
12	<b>BLM18BA121SN1</b>	10	120Ω±25%	200	0.90
13	<b>BLM18BB050SN1</b>	10	5Ω±25%	700	0.05
14	<b>BLM18BB100SN1</b>	10	10Ω±25%	700	0.10
15	<b>BLM18BB220SN1</b>	10	22Ω±25%	600	0.20
16	<b>BLM18BB470SN1</b>	10	47Ω±25%	550	0.25
17	<b>BLM18BB600SN1</b>	10	60Ω±25%	550	0.25
18	<b>BLM18BB750SN1</b>	10	75Ω±25%	500	0.30
19	<b>BLM18BB121SN1</b>	10	120Ω±25%	500	0.30
20	<b>BLM18BB151SN1</b>	10	150Ω±25%	450	0.37

Continued on the following page. 

## Chip EMI Suppression Filter Design Kits

Continued from the preceding page.

No.	Part Number	Quantity (pcs.)	Impedance typ. (at 100MHz, 20 degrees C)	Rated Current (mA)	DC Resistance (Ω) max.
21	<b>BLM18BB221SN1</b>	10	220Ω±25%	450	0.45
22	<b>BLM18BB331SN1</b>	10	330Ω±25%	400	0.58
23	<b>BLM18BB471SN1</b>	10	470Ω±25%	300	0.85
24	<b>BLM18BD470SN1</b>	10	47Ω±25%	200	0.30
25	<b>BLM18BD121SN1</b>	10	120Ω±25%	200	0.40
26	<b>BLM18BD151SN1</b>	10	150Ω±25%	200	0.40
27	<b>BLM18BD221SN1</b>	10	220Ω±25%	200	0.45
28	<b>BLM18BD331SN1</b>	10	330Ω±25%	200	0.50
29	<b>BLM18BD421SN1</b>	10	420Ω±25%	200	0.55
30	<b>BLM18BD471SN1</b>	10	470Ω±25%	200	0.55
31	<b>BLM18BD601SN1</b>	10	600Ω±25%	200	0.65
32	<b>BLM18BD102SN1</b>	10	1000Ω±25%	100	0.85
33	<b>BLM18BD152SN1</b>	10	1500Ω±25%	50	1.20
34	<b>BLM18BD182SN1</b>	10	1800Ω±25%	50	1.50
35	<b>BLM18BD222SN1</b>	10	2200Ω±25%	50	1.50
36	<b>BLM18BD252SN1</b>	10	2500Ω±25%	50	1.50
37	<b>BLM18PG300SN1</b>	10	30Ω (Typ.)	1000	0.05
38	<b>BLM18PG330SN1</b>	10	33Ω±25%	3000	0.025
39	<b>BLM18PG600SN1</b>	10	60Ω (Typ.)	500	0.10
40	<b>BLM18PG121SN1</b>	10	120Ω±25%	2000	0.05
41	<b>BLM18PG181SN1</b>	10	180Ω±25%	1500	0.09
42	<b>BLM18PG221SN1</b>	10	220Ω±25%	1400	0.10
43	<b>BLM18PG331SN1</b>	10	330Ω±25%	1200	0.15
44	<b>BLM18PG471SN1</b>	10	470Ω±25%	1000	0.20
45	<b>BLM18KG260TN1</b>	10	26Ω±25%	6000	0.007
46	<b>BLM18KG700TN1</b>	10	70Ω±25%	3500	0.022
47	<b>BLM18KG121TN1</b>	10	120Ω±25%	3000	0.030
48	<b>BLM18KG221SN1</b>	10	220Ω±25%	2200	0.050
49	<b>BLM18KG331SN1</b>	10	330Ω±25%	1700	0.080
50	<b>BLM18KG471SN1</b>	10	470Ω±25%	1500	0.130
51	<b>BLM18KG601SN1</b>	10	600Ω±25%	1300	0.150
52	<b>BLM18SG260TN1</b>	10	26Ω±25%	6000	0.007
53	<b>BLM18SG700TN1</b>	10	70Ω±25%	4000	0.020
54	<b>BLM18SG121TN1</b>	10	120Ω±25%	3000	0.025
55	<b>BLM18SG221TN1</b>	10	220Ω±25%	2500	0.040
56	<b>BLM18SG331TN1</b>	10	330Ω±25%	1500	0.070
57	<b>BLM18RK121SN1</b>	10	120Ω±25%	200	0.25
58	<b>BLM18RK471SN1</b>	10	470Ω±25%	200	0.5
59	<b>BLM18RK601SN1</b>	10	600Ω±25%	200	0.6
60	<b>BLM18RK102SN1</b>	10	1000Ω±25%	200	0.8

### ●EKEMBL8GA (Chip Ferrite Beads 0603 Size / for High Frequency Type)

No.	Part Number	Quantity (pcs.)	Impedance (at 100MHz, 20 degrees C)	Impedance (at 1GHz, 20 degrees C)	Rated Current (mA)	DC Resistance (Ω) max.
1	<b>BLM18HG471SN1</b>	10	470Ω±25%	600Ω (Typ.)	200	0.85
2	<b>BLM18HG601SN1</b>	10	600Ω±25%	700Ω (Typ.)	200	1.00
3	<b>BLM18HG102SN1</b>	10	1000Ω±25%	1000Ω (Typ.)	100	1.60
4	<b>BLM18HB121SN1</b>	10	120Ω±25%	500Ω±40%	200	0.50
5	<b>BLM18HB221SN1</b>	10	220Ω±25%	1100Ω±40%	100	0.80
6	<b>BLM18HB331SN1</b>	10	330Ω±25%	1600Ω±40%	50	1.20
7	<b>BLM18HD471SN1</b>	10	470Ω±25%	1000Ω (Typ.)	100	1.20
8	<b>BLM18HD601SN1</b>	10	600Ω±25%	1200Ω (Typ.)	100	1.50

Continued on the following page.

# Chip EMI Suppression Filter Design Kits

 Continued from the preceding page.

No.	Part Number	Quantity (pcs.)	Impedance (at 100MHz, 20 degrees C)	Impedance (at 1GHz, 20 degrees C)	Rated Current (mA)	DC Resistance (Ω) max.
9	<b>BLM18HD102SN1</b>	10	1000Ω±25%	1700Ω (Typ.)	50	1.80
10	<b>BLM18HE601SN1</b>	10	600Ω±25%	600Ω (Typ.)	800	0.25
11	<b>BLM18HE102SN1</b>	10	1000Ω±25%	1000Ω (Typ.)	600	0.35
12	<b>BLM18HE152SN1</b>	10	1500Ω±25%	1500Ω (Typ.)	500	0.50
13	<b>BLM18HK331SN1</b>	10	330Ω±25%	400Ω (Typ.)	200	0.50
14	<b>BLM18HK471SN1</b>	10	470Ω±25%	600Ω (Typ.)	200	0.70
15	<b>BLM18HK601SN1</b>	10	600Ω±25%	700Ω (Typ.)	100	0.90
16	<b>BLM18HK102SN1</b>	10	1000Ω±25%	1200Ω (Typ.)	50	1.50
17	<b>BLM18EG101TN1</b>	10	100Ω±25%	140Ω (Typ.)	2000	0.045
18	<b>BLM18EG121SN1</b>	10	120Ω±25%	145Ω (Typ.)	2000	0.04
19	<b>BLM18EG221TN1</b>	10	220Ω±25%	300Ω (Typ.)	1000	0.15
20	<b>BLM18EG221SN1</b>	10	220Ω±25%	260Ω (Typ.)	2000	0.05
21	<b>BLM18EG331TN1</b>	10	330Ω±25%	450Ω (Typ.)	500	0.21
22	<b>BLM18EG391TN1</b>	10	390Ω±25%	520Ω (Typ.)	500	0.30
23	<b>BLM18EG471SN1</b>	10	470Ω±25%	550Ω (Typ.)	500	0.21
24	<b>BLM18EG601SN1</b>	10	600Ω±25%	700Ω (Typ.)	500	0.35
25	<b>BLM18GG471SN1</b>	10	470Ω±25%	1800Ω±30%	200	1.30

## ●EKEMBL21D (Chip Ferrite Beads 0805 Size / for Large-current P Type)

No.	Part Number	Quantity (pcs.)	Impedance typ. (at 100MHz, 20 degrees C)	Rated Current (mA)	DC Resistance (Ω) max.
1	<b>BLM21AG121SN1</b>	10	120Ω±25%	200	0.15
2	<b>BLM21AG151SN1</b>	10	150Ω±25%	200	0.15
3	<b>BLM21AG221SN1</b>	10	220Ω±25%	200	0.20
4	<b>BLM21AG331SN1</b>	10	330Ω±25%	200	0.25
5	<b>BLM21AG471SN1</b>	10	470Ω±25%	200	0.25
6	<b>BLM21AG601SN1</b>	10	600Ω±25%	200	0.30
7	<b>BLM21AG102SN1</b>	10	1000Ω±25%	200	0.45
8	<b>BLM21BB050SN1</b>	10	5Ω±25%	500	0.07
9	<b>BLM21BB600SN1</b>	10	60Ω±25%	200	0.20
10	<b>BLM21BB750SN1</b>	10	75Ω±25%	200	0.25
11	<b>BLM21BB121SN1</b>	10	120Ω±25%	200	0.25
12	<b>BLM21BB221SN1</b>	10	220Ω±25%	200	0.35
13	<b>BLM21BB331SN1</b>	10	330Ω±25%	200	0.40
14	<b>BLM21BB471SN1</b>	10	470Ω±25%	200	0.45
15	<b>BLM21BD121SN1</b>	10	120Ω±25%	200	0.25
16	<b>BLM21BD221SN1</b>	10	220Ω±25%	200	0.25
17	<b>BLM21BD421SN1</b>	10	420Ω±25%	200	0.30
18	<b>BLM21BD471SN1</b>	10	470Ω±25%	200	0.35
19	<b>BLM21BD601SN1</b>	10	600Ω±25%	200	0.35
20	<b>BLM21BD102SN1</b>	10	1000Ω±25%	200	0.40
21	<b>BLM21BD152SN1</b>	10	1500Ω±25%	200	0.45
22	<b>BLM21BD182SN1</b>	10	1800Ω±25%	200	0.50
23	<b>BLM21BD222SN1</b>	10	2250Ω (Typ.)	200	0.60
24	<b>BLM21BD222TN1</b>	10	2200Ω±25%	200	0.60
25	<b>BLM21BD272SN1</b>	10	2700Ω±25%	200	0.80
26	<b>BLM21PG220SN1</b>	10	22Ω±25%	6000	0.01
27	<b>BLM21PG300SN1</b>	10	30Ω (Typ.)	3000	0.015
28	<b>BLM21PG600SN1</b>	10	60Ω±25%	3000	0.025
29	<b>BLM21PG221SN1</b>	10	220Ω±25%	2000	0.050
30	<b>BLM21PG331SN1</b>	10	330Ω±25%	1500	0.09
31	<b>BLM31PG330SN1</b>	10	33Ω±25%	6000	0.01

Continued on the following page. 

## Chip EMI Suppression Filter Design Kits

 Continued from the preceding page.

No.	Part Number	Quantity (pcs.)	Impedance typ. (at 100MHz, 20 degrees C)	Rated Current (mA)	DC Resistance (Ω) max.
32	<b>BLM31PG500SN1</b>	10	50Ω (Typ.)	3000	0.025
33	<b>BLM31PG121SN1</b>	10	120Ω±25%	3000	0.025
34	<b>BLM31PG391SN1</b>	10	390Ω (Typ.)	2000	0.05
35	<b>BLM31PG601SN1</b>	10	600Ω (Typ.)	1500	0.09
36	<b>BLM41PG600SN1</b>	10	60Ω (Typ.)	6000	0.01
37	<b>BLM41PG750SN1</b>	10	75Ω (Typ.)	3000	0.025
38	<b>BLM41PG181SN1</b>	10	180Ω (Typ.)	3000	0.025
39	<b>BLM41PG471SN1</b>	10	470Ω (Typ.)	2000	0.05
40	<b>BLM41PG102SN1</b>	10	1000Ω (Typ.)	1500	0.09

### ●EKEMNFMCB (Chip EMIFIL® Capacitor Type for Signal Lines)

No.	Part Number	Quantity (pcs.)	Capacitance	Rated Voltage (Vdc)	Rated Current (mA)	Insulation Resistance (MΩ min.)
1	<b>NFM18CC220U1C3</b>	10	22pF±20%	16	400	1000
2	<b>NFM18CC470U1C3</b>	10	47pF±20%	16	400	1000
3	<b>NFM18CC101R1C3</b>	10	100pF±20%	16	500	1000
4	<b>NFM18CC221R1C3</b>	10	220pF±20%	16	500	1000
5	<b>NFM18CC471R1C3</b>	10	470pF±20%	16	500	1000
6	<b>NFM18CC102R1C3</b>	10	1000pF±20%	16	600	1000
7	<b>NFM18CC222R1C3</b>	10	2200pF±20%	16	700	1000
8	<b>NFM18CC223R1C3</b>	10	22000pF±20%	16	1000	1000
9	<b>NFM21CC220U1H3</b>	10	22pF±20%	50	700	1000
10	<b>NFM21CC470U1H3</b>	10	47pF±20%	50	700	1000
11	<b>NFM21CC101U1H3</b>	10	100pF±20%	50	700	1000
12	<b>NFM21CC221R1H3</b>	10	220pF±20%	50	700	1000
13	<b>NFM21CC471R1H3</b>	10	470pF±20%	50	1000	1000
14	<b>NFM21CC102R1H3</b>	10	1000pF±20%	50	1000	1000
15	<b>NFM21CC222R1H3</b>	10	2200pF±20%	50	1000	1000
16	<b>NFM21CC223R1H3</b>	10	22000pF±20%	50	2000	1000

### ●EKEMFA31D (Chip EMIFIL® Capacitor Array Type/ RC Combined Array Type)

No.	Part Number	Quantity (pcs.)	Capacitance	Rated Voltage (Vdc)	Rated Current (mA)	Insulation Resistance (MΩ min.)
1	<b>NFA31CC220S1E4</b>	10	22pF±20%	25	200	1000
2	<b>NFA31CC470S1E4</b>	10	47pF±20%	25	200	1000
3	<b>NFA31CC101S1E4</b>	10	100pF±20%	25	200	1000
4	<b>NFA31CC221S1E4</b>	10	220pF±20%	25	200	1000
5	<b>NFA31CC471R1E4</b>	10	470pF±20%	25	200	1000
6	<b>NFA31CC102R1E4</b>	10	1000pF±20%	25	200	1000
7	<b>NFA31CC222R1E4</b>	10	2200pF±20%	25	200	1000
8	<b>NFA31CC223R1C4</b>	10	22000pF±20%	16	200	1000
9	<b>NFA31GD1006R84</b>	10	10pF±20%	6	50	1000
10	<b>NFA31GD1004704</b>	10	10pF±20%	6	20	1000
11	<b>NFA31GD1001014</b>	10	10pF±20%	6	15	1000
12	<b>NFA31GD4706R84</b>	10	47pF±20%	6	50	1000
13	<b>NFA31GD4703304</b>	10	47pF±20%	6	20	1000
14	<b>NFA31GD4704704</b>	10	47pF±20%	6	20	1000
15	<b>NFA31GD4701014</b>	10	47pF±20%	6	15	1000
16	<b>NFA31GD1016R84</b>	10	100pF±20%	6	50	1000
17	<b>NFA31GD1014704</b>	10	100pF±20%	6	20	1000

Continued on the following page. 

## Chip EMI Suppression Filter Design Kits

Continued from the preceding page.

No.	Part Number	Quantity (pcs.)	Capacitance	Rated Voltage (Vdc)	Rated Current (mA)	Insulation Resistance (MΩ min.)
18	NFA31GD1011014	10	100pF±20%	6	15	1000

### ●EKEMFL18E (Chip EMIFIL® LC Combined Type)

No.	Part Number	Quantity (pcs.)	Cut-off Frequency	Rated Voltage (Vdc)	Rated Current (mA)	Insulation Resistance (MΩ min.)	DC Resistance (Ω) max.
1	NFL18ST207X1C3	10	200MHz	16	150	1000	3.5
2	NFL18ST307X1C3	10	300MHz	16	200	1000	1.8
3	NFL18ST507X1C3	10	500MHz	16	200	1000	1.5
4	NFL18SP157X1A3	10	150MHz	10	100	1000	3.0
5	NFL18SP207X1A3	10	200MHz	10	100	1000	3.0
6	NFL18SP307X1A3	10	300MHz	10	100	1000	3.0
7	NFL18SP507X1A3	10	500MHz	10	100	1000	2.0
8	NFL21SP106X1C3	10	10MHz	16	100	1000	8.5
9	NFL21SP206X1C7	10	20MHz	16	100	1000	8.5
10	NFL21SP506X1C3	10	50MHz	16	150	1000	3.5
11	NFL21SP706X1C3	10	70MHz	16	150	1000	3.0
12	NFL21SP107X1C3	10	100MHz	16	200	1000	2.0
13	NFL21SP157X1C3	10	150MHz	16	200	1000	2.0
14	NFL21SP207X1C3	10	200MHz	16	250	1000	1.5
15	NFL21SP307X1C3	10	300MHz	16	300	1000	1.2
16	NFL21SP407X1C3	10	400MHz	16	300	1000	1.2
17	NFL21SP507X1C3	10	500MHz	16	300	1000	1.2

No.	Part Number	Quantity (pcs.)	Cut-off Frequency	Attenuation (dB min.)									Rated Current	Rated Voltage	
				10MHz	20MHz	50MHz	100MHz	150MHz	200MHz	300MHz	400MHz	500MHz	1GHz		
18	NFW31SP106X1E4	10	10MHz	6dB max.	5	25	25	-	25	-	-	30	30	200mA	25V
19	NFW31SP206X1E4	10	20MHz	-	6dB max.	5	25	-	25	-	-	30	30	200mA	25V
20	NFW31SP506X1E4	10	50MHz	-	-	6dB max.	10	-	30	-	-	30	30	200mA	25V
21	NFW31SP107X1E4	10	100MHz	-	-	-	6dB max.	-	5	-	-	20	30	200mA	25V
22	NFW31SP157X1E4	10	150MHz	-	-	-	-	6dB max.	-	10	20	30	30	200mA	25V
23	NFW31SP207X1E4	10	200MHz	-	-	-	-	-	6dB max.	-	-	10	30	200mA	25V
24	NFW31SP307X1E4	10	300MHz	-	-	-	-	-	-	6dB max.	-	5	15	200mA	25V
25	NFW31SP407X1E4	10	400MHz	-	-	-	-	-	-	-	6dB max.	-	10	200mA	25V
26	NFW31SP507X1E4	10	500MHz	-	-	-	-	-	-	-	-	6dB max.	10	200mA	25V

### ●EKEMFA20E (Chip EMIFIL® LC Combined Array Type)

No.	Part Number	Quantity (pcs.)	Cut-off Frequency	Rated Voltage (Vdc)	Rated Current (mA)	Insulation Resistance (MΩ min.)
1	NFA18SL137V1A45	10	130MHz	10	50	1000
2	NFA18SL187V1A45	10	180MHz	10	50	1000
3	NFA18SL207V1A45	10	200MHz	10	50	1000
4	NFA18SL307V1A45	10	300MHz	10	100	1000
5	NFA18SL407V1A45	10	400MHz	10	100	1000
6	NFA18SL487V1A45	10	480MHz	10	100	1000
7	NFA21SL506X1A48	10	50MHz	10	20	1000
8	NFA21SL806X1A48	10	80MHz	10	20	1000
9	NFA21SL207X1A45	10	200MHz	10	100	1000
10	NFA21SL207X1A48	10	200MHz	10	100	1000
11	NFA21SL307X1A45	10	300MHz	10	100	1000
12	NFA21SL307X1A48	10	300MHz	10	100	1000

Continued on the following page.

## Chip EMI Suppression Filter Design Kits

Continued from the preceding page.

No.	Part Number	Quantity (pcs.)	Cut-off Frequency	Rated Voltage (Vdc)	Rated Current (mA)	Insulation Resistance (MΩ min.)
13	<b>NFA21SL287V1A45</b>	10	280MHz	10	100	1000
14	<b>NFA21SL287V1A48</b>	10	280MHz	10	100	1000
15	<b>NFA21SL317V1A45</b>	10	310MHz	10	100	1000
16	<b>NFA21SL317V1A48</b>	10	310MHz	10	100	1000
17	<b>NFA21SL337V1A45</b>	10	330MHz	10	100	1000
18	<b>NFA21SL337V1A48</b>	10	330MHz	10	100	1000

### ●EKEMNFMPH (Chip EMIFIL® for Large Current)

No.	Part Number	Quantity (pcs.)	Capacitance	Rated Voltage (Vdc)	Rated Current (A)	Insulation Resistance (MΩ min.)
1	<b>NFM18PC104R1C3</b>	10	0.1μF±20%	16	2	1000
2	<b>NFM18PC224R0J3</b>	10	0.22μF±20%	6.3	2	1000
3	<b>NFM18PC474R0J3</b>	10	0.47μF±20%	6.3	2	1000
4	<b>NFM18PC105R0J3</b>	10	1μF±20%	6.3	2	500
5	<b>NFM18PC225B0J3</b>	10	2.2μF±20%	6.3	2	200
6	<b>NFM18PC225B1A3</b>	10	2.2μF±20%	10	4	200
7	<b>NFM18PS474R0J3</b>	10	0.47μF±20%	6.3	2	1000
8	<b>NFM18PS105R0J3</b>	10	1μF±20%	6.3	2	500
9	<b>NFM21PC104R1E3</b>	10	0.1μF±20%	25	2	1000
10	<b>NFM21PC224R1C3</b>	10	0.22μF±20%	16	2	1000
11	<b>NFM21PC474R1C3</b>	10	0.47μF±20%	16	2	1000
12	<b>NFM21PC105B1A3</b>	10	1μF±20%	10	4	500
13	<b>NFM21PC105B1C3</b>	10	1μF±20%	16	4	500
14	<b>NFM21PC225B0J3</b>	10	2.2μF±20%	6.3	4	200
15	<b>NFM21PC475B1A3</b>	10	4.7μF±20%	10	6	100
16	<b>NFE31PC276B0J3</b>	10	27μF±20%	6.3	6	20
17	<b>NFE31PT152Z1E9</b>	10	1500pF +50/-20%	25	6	1000
18	<b>NFE31PT222Z1E9</b>	10	2200pF±50%	25	6	1000
19	<b>NFE61PT102E1H9</b>	10	1000pF +80/-20%	50	2	1000
20	<b>NFE61PT472C1H9</b>	10	4700pF +80/-20%	50	2	1000
21	<b>NFM41PC204F1H3</b>	10	0.2μF +80/-20%	50	2	1000
22	<b>NFM41PC155B1E3</b>	10	1.5μF±20%	25	6	300

### ●EKEMDL21J (Chip Common Mode Choke Coils)

No.	Part Number	Quantity (pcs.)	Common Mode Impedance (at 100MHz, 20 degrees C)	Rated Voltage (Vdc)	Rated Current (mA)	Insulation Resistance (MΩ min.)
1	<b>DLW21HN670SQ2</b>	10	67Ω±25%	50	330	10
2	<b>DLW21HN900SQ2</b>	10	90Ω±25%	50	330	10
3	<b>DLW21HN121SQ2</b>	10	120Ω±25%	50	280	10
4	<b>DLW21HN181SQ2</b>	10	180Ω±25%	50	250	10
5	<b>DLW21SN670SQ2</b>	10	67Ω±25%	50	400	10
6	<b>DLW21SN900SQ2</b>	10	90Ω±25%	50	330	10
7	<b>DLW21SN121SQ2</b>	10	120Ω±25%	50	370	10
8	<b>DLW21SN181SQ2</b>	10	180Ω±25%	50	330	10
9	<b>DLW21SN261SQ2</b>	10	260Ω±25%	50	300	10
10	<b>DLW21SN371SQ2</b>	10	370Ω±25%	50	280	10
11	<b>DLW21SN670HQ2</b>	10	67Ω±25%	20	320	10
12	<b>DLW21SN900HQ2</b>	10	90Ω±25%	20	280	10
13	<b>DLW21SN121HQ2</b>	10	120Ω±25%	20	280	10
14	<b>DLW21SR670HQ2</b>	10	67Ω±25%	20	400	10

Continued on the following page.

## Chip EMI Suppression Filter Design Kits

Continued from the preceding page.

No.	Part Number	Quantity (pcs.)	Common Mode Impedance (at 100MHz, 20 degrees C)	Rated Voltage (Vdc)	Rated Current (mA)	Insulation Resistance (MΩ min.)
15	<b>DLP0NSN670HL2</b>	10	67Ω±20%	5	110	100
16	<b>DLP0NSN900HL2</b>	10	90Ω±20%	5	100	100
17	<b>DLP0NSN121HL2</b>	10	120Ω±20%	5	90	100
18	<b>DLP11SN670SL2</b>	10	67Ω±20%	5	180	100
19	<b>DLP11SN121SL2</b>	10	120Ω±20%	5	140	100
20	<b>DLP11SN161SL2</b>	10	160Ω±20%	5	120	100
21	<b>DLP11SN900HL2</b>	10	90Ω±20%	5	150	100
22	<b>DLP11SN201HL2</b>	10	200Ω±20%	5	110	100
23	<b>DLP11SN241HL2</b>	10	240Ω±20%	5	100	100
24	<b>DLP11SN281HL2</b>	10	280Ω±20%	5	90	100
25	<b>DLP11SN331HL2</b>	10	330Ω±20%	5	80	100
26	<b>DLP11SA350HL2</b>	10	35Ω±25%	5	170	100
27	<b>DLP11SA670HL2</b>	10	67Ω±25%	5	150	100
28	<b>DLP11SA900HL2</b>	10	90Ω±25%	5	150	100
29	<b>DLP2ADN670HL4</b>	10	67Ω±20%	5	140	100
30	<b>DLP2ADN900HL4</b>	10	90Ω±20%	5	130	100
31	<b>DLP2ADN121HL4</b>	10	120Ω±20%	5	120	100
32	<b>DLP2ADN161HL4</b>	10	160Ω±20%	5	100	100
33	<b>DLP2ADN201HL4</b>	10	200Ω±20%	5	90	100
34	<b>DLP2ADN241HL4</b>	10	240Ω±20%	5	80	100
35	<b>DLP2ADN281HL4</b>	10	280Ω±20%	5	80	100

### ●EKEMDCC5B (Chip Common Mode Choke Coils for DC Power Line / SMD Block type EMIFIL® for Power Line)

No.	Part Number	Quantity (pcs.)	Common Mode Impedance (at 100MHz, 20 degrees C)	Rated Voltage (Vdc)	Rated Current (mA)	Insulation Resistance (MΩ min.)
1	<b>DLW5AHN402SQ2</b>	5	4000Ω (Typ.)	50	200	10
2	<b>DLW5BSN191SQ2</b>	5	190Ω (Typ.)	50	5000	10
3	<b>DLW5BSN351SQ2</b>	5	350Ω (Typ.)	50	2000	10
4	<b>DLW5BSN102SQ2</b>	5	1000Ω (Typ.)	50	1500	10
5	<b>DLW5BSN152SQ2</b>	5	1500Ω (Typ.)	50	1000	10
6	<b>DLW5BSN302SQ2</b>	5	3000Ω (Typ.)	50	500	10
7	<b>DLW5BTN101SQ2</b>	5	100Ω (Typ.)	50	6000	10
8	<b>DLW5BTN251SQ2</b>	5	250Ω (Typ.)	50	5000	10
9	<b>DLW5BTN501SQ2</b>	5	500Ω (Typ.)	50	4000	10
10	<b>DLW5BTN102SQ2</b>	5	1000Ω (Typ.)	50	2000	10
11	<b>DLW5BTN142SQ2</b>	5	1400Ω (Typ.)	50	1500	10

No.	Part Number	Quantity (pcs.)	Insertion Loss	Rated Voltage (Vdc)	Rated Current (A)	Insulation Resistance (MΩ min.)
12	<b>BNX022-01</b>	5	1MHz to 1GHz: 35dB min.	50	10	500
13	<b>BNX023-01</b>	5	1MHz to 1GHz: 35dB min.	100	15	500